

Project:
Type:
Date:
Product Code:
Approval:



BRLS

Strip LED retrofit kit, offering up to 50% in energy savings. It has been designed to convert existing 4ft and 8ft Commercial or Industrial strip fixtures from T8 or T12 to LED. Its flexibility and simple installation make it easy to take advantage of improved energy-efficiency and performance.

FEATURES

- Has a full range of voltage options from 120-277V and 347V
- L70 of 200,000 hours
- Fixture lensing provides an even light distribution through the use of 120-degree angle LED chips and a specially designed lens

OPTIONS

- 0 – 10V dimming standard
- Available in 3000K, 3500K, 4000K, and 5000K
- Lumen packages are available in 2000 to 8000 lumens

APPLICATIONS

- Existing fluorescent strip style fixtures

WARRANTY

- Standard 5 year system, and 10 year LED warranty

OPTICS

High-efficiency diffuser maximizes light distribution while providing diffusion of LED point sources.

ELECTRICAL

All components are UL recognized

MOUNTING

Holes provided for mounting inside existing fluorescent strip fixtures using self-tapping screws.

CONSTRUCTION




- Fixture materials are precision bent for added strength and rigidity
- Shallow design for ease of installation and a clean, professional look.

APPROVAL



- ETL Certified
- DLC Certified

PRODUCT DIMENSIONS

End View



Side View



SPECIFICATIONS MAY CHANGE WITHOUT NOTICE



PRODUCT KEY

Retrofit Type	Fixture Length	Fixture Width	Fixture Type	Lumen Output	CRI & Colour Temperature	Driver Voltage	
BRLS		W		L			
	4	2.75/3	Blank - T8	4'	830	UNV	
	8	3.25/4	T5		2.5	835	347
		4.25/5			3	840	
					3.5	850	
				4'/8'	4		
				8'	4.5		
					5		
					5.5		
					6		
					6.5		
					7		
				7.5			
				8			

SPECIFICATIONS MAY CHANGE WITHOUT NOTICE

